


Interior installation

Rail systems



TS assembly block

Installation in the vertical TS, SE enclosure sections for mounting PS-compatible individual components.

Material:

- Die-cast zinc

Supply includes:

- Assembly screws

Packs of	Model No.
4 pc(s).	8800.310

Possible alternative:

- Snap-on nut, see page 618



Adaptor rail

for PS compatibility

Installation in the vertical TS, SE enclosure sections (across the entire enclosure height or in sub-sections), and in the case of SE, may additionally be fitted to the top horizontal section in the width (must be cut to length depending on the width of the enclosure), in order to achieve compatibility with:

- PS punched rail, 23 x 23 mm
- PS punched section without mounting flange, 23 x 73 mm
- PS punched section with mounting flange, 23 x 73 mm

Material:

- Sheet steel

Surface finish:

- Zinc-plated

Supply includes:

- Assembly screws


For enclosure height mm	Packs of	Model No.
1800	4 pc(s).	8800.380
2000	4 pc(s).	8800.300
2200	4 pc(s).	8800.320

Accessories:

- Screws, see page 625

Possible alternative:

- Snap-on nut, see page 618



PS punched rails 23 x 23 mm

for TS, SE

Installation options:

- On the vertical enclosure section
 - Directly via support brackets TS
 - Via adaptor rail for PS compatibility in conjunction with angle brackets, mounting brackets or support brackets PS
- On the horizontal enclosure section
 - Directly via angle brackets, mounting brackets or support brackets PS

Material:

- Sheet steel

Surface finish:

- Zinc-plated

Length mm	For WHD mm	Packs of	Model No.
295	400	12 pc(s).	4169.000
395	500	12 pc(s).	4170.000
495	600	12 pc(s).	4171.000
695	800	12 pc(s).	4172.000
895	1000	12 pc(s).	4173.000
1095	1200	6 pc(s).	4174.000
1295	1400	6 pc(s).	4393.000
1495	1600	6 pc(s).	4175.000
1695	1800	6 pc(s).	4176.000
1895	2000	6 pc(s).	4177.000
2095	2200	6 pc(s).	4178.000

Also required:

- U nuts, see page 624
- Mounting brackets TS/PS, see page 619 or
- Angle brackets, support brackets TS/PS, see page 620

Accessories:

- Cable attachment, see page 667
- Screws, see page 625
- Cable tie for fast assembly 2597.000, see page 667

Configuration examples:

See from page 598

